

```
when led1OnButton .Click
do call [ESP8266WebViewer v].GoToUrl
    url join call [ESP8266IpTinyDB v].GetValue
        tag "esp_ip"
        valueIfTagNotThere "ON1"
    call [ESP8266IpTinyDB v].StoreValue
        tag "led1State"
        valueToStore "(state on)"
    set [led1StatusLabel v].Text to call [ESP8266IpTinyDB v].GetValue
        tag "led1State"
        valueIfTagNotThere "ON1"
```

```
when led1OffButton .Click
do call [ESP8266WebViewer v].GoToUrl
    url join call [ESP8266IpTinyDB v].GetValue
        tag "esp_ip"
        valueIfTagNotThere "OFF1"
    call [ESP8266IpTinyDB v].StoreValue
        tag "led1State"
        valueToStore "(state off)"
    set [led1StatusLabel v].Text to call [ESP8266IpTinyDB v].GetValue
        tag "led1State"
        valueIfTagNotThere "OFF1"
```

```
when led2OnButton .Click
do call [ESP8266WebViewer v].GoToUrl
    url join call [ESP8266IpTinyDB v].GetValue
        tag "esp_ip"
        valueIfTagNotThere "ON2"
    call [ESP8266IpTinyDB v].StoreValue
        tag "led2State"
        valueToStore "(state on)"
    set [led2StatusLabel v].Text to call [ESP8266IpTinyDB v].GetValue
        tag "led2State"
        valueIfTagNotThere "ON2"
```

```

when led2OffButton .Click
do call ESP8266WebViewer .GoToUrl
    url join call ESP8266IpTinyDB .GetValue
        tag " esp_ip "
        valueIfTagNotThere " OFF2 "
    " OFF2 "
call ESP8266IpTinyDB .StoreValue
    tag " led2State "
    valueToStore " (state off) "
set led2StatusLabel .Text to call ESP8266IpTinyDB .GetValue
    tag " led2State "
    valueIfTagNotThere " OFF2 "

```

```

when setIpButton .Click
do set saveHorizontalArrangement .Visible to true
set setIpHorizontalArrangement .Visible to false

```

```

when Screen1 .Initialize
do set ESP8266IpInfoLabel .Text to call ESP8266IpTinyDB .GetValue
    tag " esp_ip "
    valueIfTagNotThere " "
set led2StatusLabel .Text to call ESP8266IpTinyDB .GetValue
    tag " led2State "
    valueIfTagNotThere " "
set led1StatusLabel .Text to call ESP8266IpTinyDB .GetValue
    tag " led1State "
    valueIfTagNotThere " "

```

```

when SAVE .Click
do call ESP8266IpTinyDB .StoreValue
    tag " esp_ip "
    valueToStore join " http:// "
        TextBox1 .Text
        " /?pin= "
set ESP8266IpInfoLabel .Text to call ESP8266IpTinyDB .GetValue
    tag " esp_ip "
    valueIfTagNotThere " "
set saveHorizontalArrangement .Visible to false
set setIpHorizontalArrangement .Visible to true

```

when `exit_btn` .Click

do `close application`